

Marschalling patchboard PTMC 1,5-3 /RD

500 V, 17.5 A, 0.14 - 2.5, AWG: 12 - 26, pole:1, Number of connections: 6, 11 x 12.2 mm, grey,elements: red,



Technical Data

Netto depth (mm)	30,00
Net width (mm)	11,00
Net height (mm)	12,20
EAN	4055626114071
Power loss (W)	0,56
Min. ambient temperature (°C)	-40
Max. ambient temperature (°C)	120
Basic Description	Terminal
System	Push-In
Series	PT
Version	Marschalling patchboard
Max. cross section, solid wire (mm²)	2,50
Max. cross section, flexible wire (mm²)	1,50
Max. cross section, flexible wire with ferrule (mm²)	1,50
Min. cross section, solid wire (mm²)	0,14
Min. cross section, flexible wire (mm²)	0,14
Min. cross section, flexible wire with ferrule (mm²)	0,14

Technical Data - continued

Cross-section (mm²)	1.5
Colour	Red
Rated current (A)	17,50

Article Table

DESCRIPTION	Order No.
Marschalling patchboard PTMC 1,5-3 /RD 500 V, 17.5 A, 0.14 - 2.5, AWG: 12 - 26, pole:1, Number of connections: 6, 11 x 12.2 mm, grey,elements: red,	IP3270421
Optional Accessories	
End bracket CLIPFIX 15, to be snapped onto NS 15 DIN rail Snap-on end bracket, color: gray	IP3022263
End bracket CLIPFIX 35-5, for NS 35/7,5 or NS 35/15 Quick mounting end clamp, with marking option, width: 5.15 mm, color: gray	IP3022276
End bracket CLIPFIX 35, for NS 35/7,5 DIN rail or NS 35/15 Quick mounting end clamp, with marking option, width: 9.5 mm, color: gray	IP3022218
End bracket E/UK End clamp, Width: 9.5 mm, Height: 35.3 mm, Length: 50.5 mm, Color: gray	IP1201442
End bracket E/UK 1 End clamps, for supporting the ends of double-level and three-level terminal blocks, width: 10 mm, color: gray	IP1201413
End bracket E/MBK End clamp, width: 6.2 mm, color: gray	IP1401637
End bracket E/MK 1 End clamp width: 6 mm, color: gray	IP1421659
End bracket E/NS 35 N End clamp, width: 9.5 mm, color: gray	IP0800886
Marking tags for TB and ST - terminals, 1-30 (each 2x) Marking tags for Phoenix Contact - terminals, series TB and ST	IP196001
Marking tags for TB and ST - terminals, 31-60 (each 2x) Marking tags for Phoenix Contact - terminals, series TB and ST	IP196031
Marking tags for TB and ST - terminals, 61-90 (each 2x) Marking tags for Phoenix Contact - terminals, series TB and ST	IP196061
Marking tags for TB and ST - terminals, 91-120 (each 2x) Marking tags for Phoenix Contact - terminals, series TB and ST	IP196091

Article Table

DESCRIPTION	Order No.
Optional Accessories	
Marking tags for TB and ST - terminals, 121-150 (each 2x)	IP196121
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 151-180 (each 2x)	IP196151
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 181-210 (each 2x)	IP196181
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 211-240 (each 2x)	IP196211
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 241-270 (each 2x)	IP196241
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 271-300 (each 2x)	IP196271
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 301-330 (each 2x)	IP196301
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 331-360 (each 2x)	IP196331
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 361-390 (each 2x)	IP196361
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 391-420 (each 2x)	IP196391
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 421-450 (each 2x)	IP196421
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 451-480 (each 2x)	IP196451
Marking tags for Phoenix Contact - terminals, series TB and ST	
Marking tags for TB and ST - terminals, 481-510 (each 2x)	IP196481
Marking tags for Phoenix Contact - terminals, series TB and ST	